


Wireless Push-Button 2 channels, surface mount

Product ref.: 131774
PRODUCT FEATURES



- Flexible push-button with two channels for central control of connected Homematic devices
- All Homematic actuators can be taught-in directly
- LED signals sending and confirmation of commands and gives information about error messages
- Easy to integrate into existing switches from the following manufacturers: Berker (S.1, B.1, B.3, B.7 Glas), GIRA (System 55, Standard 55, E2, E22, Event, Esprit), Merten (1-M, Atelier-M, M-Smart, M-Arc, M-Star, M-Plan), JUNG (A 500, AS 500, A plus, A creation) and ELSO (Joy)
- Can also be mounted in the clip-on frame supplied
- Can be positioned anywhere by screwing or sticking it in place
- It is e.g. possible to switch lights on and off or dim lights brighter or darker

TECHNICAL SPECIFICATIONS

Supply voltage:	2x 1.5 V LR03/micro/AAA
Battery life:	5 years (typ.)
Degree of protection:	IP20
Ambient temperature:	-10°C to +55°C
Dimensions (W x H x D):	86 x 86 x 16.5 mm
Weight:	61.4 g (not incl. battery)
Radio frequency:	868.3 MHz
Typ. open area RF range:	100 m

LOGISTIC DATA

Product reference:	131774
EAN code:	4047976317745
Short description:	HM-PB-2-WM55-2
Packing unit:	90
Packaging dimensions:	122 x 112 x 48 mm
Total weight:	163.9 g

PACKAGE CONTENTS

Wireless Push-Button 2-channels
2x 1.5 V LR03/micro/AAA
Rocker
Mounting material (2x screws, 2x plugs, 2x adhesive strips, 1x mounting plate)
Operating manual in DE and EN