

Starter Set Light



Product ref.: 151671A0



Product features

- Starter set for comfortable light control
- The Access Point connects the smartphone via the Homematic IP cloud with all Homematic IP devices
- The pluggable dimmer allows dimming and switching of various dimmable LED lamps, dimmable energy-saving lamps, LV and HV halogen lamps as well as incandescent lamps
- Easy operation via the Homematic IP app, Homematic IP Remote Control or directly on the device itself
- Individual configuration of week profiles allows dimming and switching of lights in a time-controlled manner
- The Homematic IP app offers infinitely variable dimming of connected lights
- With the wake-up light the lamp slowly and comfortably gets brighter from 0 to 100 % within 20 minutes
- Highly reliable radio protocol based on 868 MHz
- High security thanks to comprehensive AES encryption and server location in Germany - requires no personal data
- Comfortable and individual voice control (e.g. via Amazon Alexa or Google Assistant)
- The starter set light can be expanded into a comprehensive smart home system at any time together with various different Homematic IP devices

Technical specifications (per device)

Access Point:

Supply voltage	Power supply unit (5 VDC)
Ambient temperature	5 to 35 °C
Dimensions (W x H x D)	118 x 104 x 26 mm
Typical open area RF range	400 m

Pluggable Dimmer:

Supply voltage	230 V/50 Hz
Switching capacity	3 to 80 VA
Dimming method	Reverse phase control
Load type	ohmic and capacitive lamp load
Ambient temperature	-10 to 35 °C
Dimensions (W x H x D)	70 x 70 x 39 mm (not incl. mains plug)
Typ. open area RF range	170 m

For further technical details and information please refer to the data sheet of the respective device

Logistical data

Product reference	151671A0
EAN code	4047976516711
Short description	HmlIP-SK6
Packing unit	6
Packing dimensions	325 x 194 x 150 mm
Weight incl. packaging	1152.0 g

Package contents

Access Point (plug-in mains adapter, network cable)
Pluggable Dimmer (2x)
Mounting accessories
User manuals