

# Pluggable Switch and Meter

Product ref.: 140666A0



## Product features

- The pluggable switch and meter enables switching of connected devices, as for example floor lamps or electric heaters
- Additionally measures energy consumption, power, voltage and current
- Can be used to extend the wireless range of the radio signal
- High measuring accuracy for measuring also stand-by loads
- Precise regulation of electric radiators in connection with a Homematic IP Wall Thermostat
- Manual operation: Connected devices can be switched on or off also directly on the device
- Low current consumption
- Thanks to the compact design, the device does not block the surrounding sockets
- Comfortable and individual voice control (e.g. via Amazon Alexa or Google Assistant)
- For operation, the Homematic IP Access Point in connection with the Homematic IP app (no recurring costs), the Homematic Central Control Unit CCU2 or an appropriate partner solution is required

## Technical specifications

Supply voltage	230 V/50 Hz
Current consumption	16 A max.
Standby power consumption	< 0.3 W
Max. switching capacity	3680 W
Measuring accuracy (power)	measuring range: 0 to 3680 W resolution: 0.01 W accuracy: 1 % ± 0.03 W*
Load type	ohmic load, $\cos\phi \geq 0.95$
Degree of protection	IP20
Ambient temperature	-10 to +35 °C
Dimensions (W x H x D)	70 x 70 x 39 mm (not incl. mains plug)
Weight	154 g
Radio frequency	868.3 MHz/869.525 MHz
Typ. open area RF range	400 m

## Logistical data

Product reference	140666A0
EAN code	4047976406661
Short description	HMIP-PSM
Packing unit	45
Packing dimensions	122 x 112 x 97 mm
Weight incl. packaging	292.4 g

## Package contents

Homematic IP Pluggable Switch and Meter

Operating manual in DE, EN, NL and FR