

Wireless Status Monitor LED16

Product ref.: 104798
PRODUCT FEATURES



- Comfortable status display and visualisation in conjunction with the Homematic Central Control Unit CCU2, without the need of a PC and/or monitor display
- 16 channel display for device status and/or system variables
- Display of home status- e.g. present/absent, alarm active/inactive, all windows closed – or the status of CCU system programs via system variables
- Multi colour LED display signals up to 4 states (red, green, orange, and off)
- 3 buttons for activation of up to 16 CCU programs, also for changing system variables (e.g. “pond pump in timer operation”)
- Display brightness can be adjusted in 16 steps via software
- Display eco mode switches LED display automatically off (duration can be adjusted)

TECHNICAL SPECIFICATIONS

Supply voltage:	7.5 VDC
Current consumption:	250 mA max.
Standby power consumption:	0.45 W
Degree of protection:	IP20
Ambient temperature:	5 to 35 °C
Dimensions (W x H x D):	110 x 100 x 15 mm
Weight:	122 g
Radio frequency:	868.3 MHz
Typ. open area RF range:	200 m

LOGISTIC DATA

Product reference:	104798
EAN code:	4047976047987
Short description:	HM-OU-LED16
Packing unit:	90
Packaging dimensions:	184 x 140 x 73 mm
Total weight:	359.4 g

PACKAGE CONTENTS

Homematic Wireless Status Monitor LED16
Mounting material (1 x screws 3.0 x 30 mm, 1 x plugs 5 mm)
1 x Power supply unit
Operating manual in DE and EN