

## Wireless Sensor for Electrical Pulses



Product ref.: 84016  
**PRODUCT FEATURES**



- Sensor for non-contact evaluation of electric DC pulses
- Controls connected Homematic devices when a previously taught-in pulse sequence is detected - this enables a Homematic actuator to be triggered by means of evaluating the headlight flasher signals of a car, so that an electrical garage door can be opened or closed
- Sensor can be controlled without great programming or installation effort
- Flexible and location-independent thanks to battery operation
- Two isolated switching channels for ON time of 1 sec or 3 min

### TECHNICAL SPECIFICATIONS

Supply voltage:	2x 1.5 V LR03/micro/AAA
Battery life:	7 years (typ.)
Degree of protection:	IP20
Dimensions (W x H x D):	90 x 40 x 24 mm
Antenna:	70 mm
Weight:	41 g (not incl. battery)
Typical open area RF range:	100 m
Radio frequency:	868.3 MHz

### LOGISTIC DATA

Product reference:	84016
EAN code:	4047976840168
Short description:	HM-Sen-EP
Packing unit:	72
Packaging dimensions:	184 x 93 x 48 mm
Total weight:	154.0 g

### PACKAGE CONTENTS

Wireless Sensor for Electrical Pulses  
 2x LR03/micro/AAA batteries  
 Operating manual in DE and EN