

Wireless Siren with signal light



Product ref.: 142478A0
PRODUCT FEATURES



- Reliable audible and visual signal output in alarm cases via high-performance piezo speaker and signal lamp
- Offers a wide range of applications and controlling options via 4 channels
- The exterior and/or interior of a building can be monitored
- Device is controlled and alarms are triggered via Homematic remote controls and sensors (e.g. Homematic Wireless Motion Detector or Wireless Window Sensor)
- Individual adjustments to personal needs via Homematic Central Control Unit - select e.g. between different alarm tones or alarm duration
- Easy and flexible mounting on walls

TECHNICAL SPECIFICATIONS

Supply voltage:	2x 1.5 V LR14/baby/C
Battery life:	2 years (typ.)
Volume:	>85 dB in 3 m distance
Current consumption:	200 mA max.
Standby power consumption:	max. 0.1 mA
Degree of protection:	IP20
Dimensions (W x H x D):	60 x 155 x 69 mm
Weight:	323 g (incl. batteries)
Radio frequency:	868.3 MHz
Typ. open area RF range:	160 m

LOGISTIC DATA

Product reference:	142478A0
EAN code:	4047976424788
Short description:	HM-Sec-Sir-WM
Packing unit:	32
Packaging dimensions:	184 x 140 x 73 mm
Total weight:	505.0 g

PACKAGE CONTENTS

Homematic Wireless Siren with signal light
2x 1.5 V LR14/baby/C batteries
Mounting material (2x screws and 2x plugs)
Wall mounting bracket
Operating manual in DE and EN