

Eco Switch





Product features

- Save energy in every room at the touch of a button: Whenever you
 leave home, all MAX! Radiator Thermostats can be brought down to an
 individually defined reduction temperature. When coming back, you can
 activate the individually defined week programs of your radiator thermostats again also at the touch of a button
- Thanks to battery operation highly flexible where mounting and selecting a mounting location are concerned
- The mounting plate can be easily screwed or attached with adhesive strips to the wall using the supplied clip-on frame or you can integrate the device into existing switches from the following manufacturers:
 Berker (S.1, B.1, B.3, B.7 Glas), GIRA (System 55, Standard 55, E2, E22, Event, Esprit), Merten (1-M, Atelier-M, M-Smart, M-Arc, M-Star, M-Plan) and JUNG (A 500, AS 500, A plus, A creation), ELSO (Joy)
- Long battery life of up to 5 years (alkaline batteries)
- Individual adjustment of button functions via MAX! software

Technical specifications

Supply voltage: 2x 1.5 V LR03/micro/AAA batteries

Current consumption: 50 mA max. Battery life: 5 years (typ.)

Degree of protection: IP20

Dimensions (W x H x D): 86 x 86 x 21.5 mm (incl. frame)

Weight: 85 g (incl. batteries)

Radio frequency: 868.3 MHz Typ. open area RF range: > 100 m

Logistical data

Product reference: 99011

EAN code: 4047976990115 Short description: BC-PB-2-WM-2

Packing unit: 90

Packing dimensions: 122 x 112 x 48 mm

Total weight: 184 g

Package contents

1x MAX! Eco Switch

2x 1.5 V LR03/micro/AAA batteries

1x Clip-on frame

1x Mounting plate

6x Screws 2x Plugs

2x Adhesive strips

1x Operating manual in DE/EN (further languages on request)



www.eQ-3.de